

USM-2 32A/63A 400V



USM-2, 32A 400V



USM-2, 63A 400V

VARENDR.	TYPE
73047	Minisentral USM-2 32A* 400V 00128-R
73061	Minisentral USM-2 63A* 400V 01118-R
73062	Minisentral USM-2 63A** 400V 01118-R

* Felles jordfeilbryter

** Jordfeilbryter på alle kurser

VARENDR.	RESERVEDELER
70006	Stativ/fot til USM-2
75247	Sikringsvindu PCE 12 moduler
75222	Apparatinntak innfelt 463-6
75220	Apparatinntak innfelt 432-6
75211	Stikkontakt innfelt rett 463-6
75207	Stikkontakt innfelt rett 432-6
75203	Stikkontakt innfelt rett 416-6
75200	Stikkontakt innfelt 2/16+j (Schuko)
75106	ABB automatsikring C 32A 4P
75105	ABB automatsikring C 16A 4P
75101	ABB automatsikring C 16A 2P
75116	ABB jordfeilbryter 63A/30mA 4P
75115	ABB jordfeilbryter 40A/30mA 4P
75113	ABB jordfeilautomat C 32A/30mA 4P
75112	ABB jordfeilautomat C 16A/30mA 4P
75124	ABB jordfeilautomat C 16A/30mA 2P

- **Vekt:** 9 kg
- **Kapasitet:** 32A 400V 22kW
63A 400V 43kW
- **Mål:** 294x559x273mm (BxHxD)
- **Vern 400V**

73047

ABB aut.sikring C 16A 4P 2 stk.
ABB aut.sikring C 16A 2P 4 stk.
ABB j.f.bryter 40A/30mA 1 stk.

73061

ABB aut.sikring C 32A 4P 1 stk.
ABB aut.sikring C 16A 4P 1 stk.
ABB aut.sikring C 16A 2P 4 stk.
ABB j.f.bryter 63A/30mA 4P 1 stk.
ABB j.f.bryter 40A/30mA 4P 1 stk.

73062

ABB j.f.automat C 32A/30mA 4P 1 stk.
ABB j.f.automat C 16A/30mA 4P 1 stk.
ABB j.f.automat C 16A/30mA 2P 4 stk.

- **Antall kW som kan føres i kabel 400V**

3x2,5+N+j	416-6	11kW
3x6+N+j	432-6	22kW
3x16+N+j	463-6	43kW
3x35+N+j	4125-6	86kW

Bestykning

32A 400V 00128-R



63A 400V 01118-R



Andre bestykninger på forespørsel.